http://www.digikey.com
00.34 P14-8RHT6-M CONN RING 14-18 (PANDUIT)

HW5
P14-8RHT
PAD1 PAD — BLUE/ORANGE
PAD3 PAD — BLUE
PAD2 PAD — BLACK
HW1
0009503031
HW2
0008580110
J3
0026605030
V12.0
C8 .1UF
C14 .1UF
LAMP_DRIVE
VCC
C20 .01UF
C21 .01UF
U4$0
U5$0
POS
LMV321
U4$1 LMV321
VERTICAL 10-TURN POT
FITS USING VIA
BOURNS 3266W-502LF-ND
C4 .01UF
R8 4.99K
10K R1
R14 100
R16 100
R15 100K
C15 .01UF
U5$1 LMV321
R18 10
R19 10
J3S
SJ-2524
RING
TIP
SLEEVE
SLAVE IN
REMOTE
DIM
CONTROL
LOUT
LIN
J3M
N/A
MASTER OUT
REMOTE
DIM
CONTROL
C18 .01UF
C19 .01UF
PB04
PA1
PA4
PA5
U6$2
ANA0 PB0
ANA1 PB1
ANA2 PB2
ANA3 PB3
ANA4/7 PB4
AVDD
AVSS
VREF
C23 .01UF
J2
SJ-3524
R2 100
R3 100
R12 10.0K
U3$2 74LVC2G14
U3$1 74LVC2G14
R17 330
LTL-4223
D1
C5 .01UF
U3$0 74LVC2G14
U6$1
PA0 T0IN
PA1 T0OUT
PA2 DE0
PA3 CTS0*
PA4 RXD0
PA5 TXD0
PA6 SCL
PA7 SDA
U6$3
T1IN PC0
T1OUT PC1
SS PC2
SCK PC3
MOSI PC4
MISO PC5
V12.0
Q2
DMP6023LE
125mOhm ZXMP6A17GTA
28mOhm DMP6023LE
R11 4.99K
GATE
R10 2.49K
DRIVE
Q1
ZXMN6A07
R9 10.0K
L1A 1mH
L1
N/A
C12 100PF
DS1
SMS290
R13 47
C13 .1UF
C17 10UF/25V
J1P
825-22-004-10-004101
J1
75869-131LF
R7 10.0K
R6 10.0K
8Kx8 FLASH
1Kx8 SRAM
18.432MHz
U6$0
Z8F0822
X1
ECS-184-18-4X
XIN
XOUT
VDD
VSS
DBG
RESET
C25 10PF
C24 10PF
C2 .01UF
U2$1
74LVC1G11
D4
BAV99
R4 10.0K
C1 10UF
R5 10.0K
SW2
KMR221
C22 .01UF
C16 .01UF
U2$0
C3 .01UF
STANDALONE:
J3S CONNECTS LEVEL/U4 TO U5/U1
(OR INSTALL 0 OHM AT R16)
DIM CONTROL LOCAL
MASTER:
J3S CONNECTS LEVEL/U4 TO U5/U1
DIM CONTROL LOCAL
SLAVE:
J3S ISOLATES LEVEL/U4 FROM U5/U1
DIM CONTYROL REMOTE
VR1 LT1117CST-3.3
VIN
VOUT
GND
VOUT1
C10 10UF/25V
C11 .1UF
C6 .01UF
C26 .01UF
C7 .1UF
C9 10UF
PAD
TP1
PCB1
102-73192
THIS BOARD CONTAINS
STATIC SENSITIVE
DEVICES. HANDLE
ONLY IN STATIC SAFE
ENVIRONMENT
MARK ZERO POINT FOR
PICK & PLACE FILE ON
PRINTED CIRCUIT BOARD

TOP_FULL — DRAWING FRAME SHOWN ON CIRCUIT BOARD
BOARD ASSY — DRAWING FRAME SHOWN ON CIRCUIT BOARD
BOT_COMPACT — DRAWING FRAME SHOWN ON CIRCUIT BOARD
BOARD-ID — DRAWING FRAME SHOWN ON CIRCUIT BOARD

PWA RELEASED AS 2D354 102-73192-B
PWB RELEASED AS 2D354 102-73192-B

Drawn	KC0JFQ	2020-06-19
Designed	KC0JFQ	2020-06-19

The University of Iowa
Department of Physics & Astronomy
Iowa City, IA, USA

TITLE: COURTESY DIMMER
A102_73192_B

CAGE	Series		Number	Rev
2D354	102	BLINKING CHIP	73192	B

Date: 4/20/24 8:06 PM 4/20/24 8:07 PM
Sheet: 1/1